



**WSF 9 & 9A FLEXIBLE SHAFT MACHINES  
PARTS LISTING**

Key No.	Part No.	Description	Price	Key No.	Part No.	Description	Price
1	SF 52	Base with casters	10.00	28	SF 13	Collar	.50
2	SF 160	Swivel stud & nuts	1.50	29	SF 29	Housing	3.00
3	T - 63	Thrust Bearing	.45	30	F 107N	Spindle	1.75
4	SF 5	Motor Plate	3.00	31	SF 26	Adjusting Collar	2.25
5	F 103	Bearing Bracket Supp.	5.00	32	F 108	Adapter	2.25
6	F 102	Bearing Bracket	5.00	33	DP 123	Lock Handle	.25
7	F112	Bearing Brack. Guide	.50	34	SF 39	Bakelite Washer	.10
8	F 111	Adjusting Screw	1.00	35	SF 25	Spacer	1.00
9	F 117	Machined Washer	.10	36	Conn.	1/4-20x1/4" Allen Screw (3)	ea. .10
10	IDS 56	Screw Knob	.35	37	B 4-A	Grease Cup	.35
11	F 113	Lock Screw	.25	38	SF 22	Housing Cap	2.00
12	CS 33-S	Hand Knob	.45	40	WSF 116	CASING	7.50
13	F 106	Shaft Holder	.50	41	WSF 117	5/16" CORE	4.25
14	F110	Shaft Holder Pin	.35	42	WSF 117S	1/4" CORE	4.25
15	F 105	Motor Pulley	4.50	44	WAC 4	HANDPIECE consists of;	16.00
16	5279	"V" Belt	.75	45	SF 180	Spindle	4.50
17	Comm.	5/16-18x5/16 Allen Screw	.10	46	SF 180C	Collar	1.50
18	"	3/8-16x3/8 Allen Screw	.10	47	382 YLC 3	Ball Bearing (2)	1.50
19	"	5/16-18x1" Hex Bolt	.15	48	SF 111	Housing	3.00
20	"	5/16-18 Hex Nut (4)	ea. .10	49	SF 180-3	Rubber Cover	1.00
21	"	5/16" I.D. Flat Washer	.05	50	SF 112	Spacer	1.00
22	"	1/4-20 Hex Jam Nut (2)	ea. .05	51	SF 178	Casing Adapter	1.00
24	F 115-A	Bearing Assembly consists of;		52	SF 131	Shaft Adapter	1.50
25	SF 59	Bearing Collar	1.25	53	SF 119-W	Fibre Washer (2)	ea. .05
26	F 104	Drive Pulley	2.50	54	SF 177-C	1/4" Collet	2.50
27	I-70336-C003	Ball-Bearing (2)	ea. 1.50	55	SF 177-N	Collet Nut	1.00

(MOTOR AS SPECIFIED)

## Walker-Turner Company, Inc.

PLAINFIELD

The Walker-Turner Company reserves the right to make changes in design or to make additions to or improvements in its products without imposing any obligation upon itself to install them on its product previously manufactured.

New Jersey, U.S.A.